



HAL
open science

DC-100-GHz Frequency Doublers in InP DHBT Technology

Vincent Puyal, Agnieszka Konczykowska, Pascal Nouet, Serge Bernard,
Sylvain Blayac, Filipe Jorge, Muriel Riet, Jean Godin

► **To cite this version:**

Vincent Puyal, Agnieszka Konczykowska, Pascal Nouet, Serge Bernard, Sylvain Blayac, et al.. DC-100-GHz Frequency Doublers in InP DHBT Technology. *IEEE Transactions on Microwave Theory and Techniques*, 2005, 53 (4), pp.1338-1344. 10.1109/TMTT.2005.845766 . lirmm-00105306

HAL Id: lirmm-00105306

<https://hal-lirmm.ccsd.cnrs.fr/lirmm-00105306v1>

Submitted on 11 Oct 2006

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

DC–100-GHz Frequency Doublers in InP DHBT Technology

Vincent Puyal, *Student Member, IEEE*, Agnieszka Konczykowska, *Senior Member, IEEE*,
Pascal Nouet, *Member, IEEE*, Serge Bernard, *Member, IEEE*, Sylvain Blayac, Filipe Jorge, Muriel Riet, and
Jean Godin

Abstract—Broad-band monolithic integrated active frequency doublers operating in dc-100-GHz frequency range are presented. Circuits are fabricated in a self-aligned InP double heterojunction bipolar transistor process. Three integrated doubler versions have been designed. Inductive peaking and active splitting effects are quantified and compared. Circuit measurements give sinusoidal output waveform at 100 GHz with an rms timing jitter of 400 fs. Circuits have a maximum conversion gain of +1 dB at 60 GHz. The fundamental suppression is better than 24 dB in the whole frequency range.

Index Terms—Active splitter, doubler, frequency multiplier, Gilbert cell, InP double heterojunction bipolar transistor (DHBT).

I. INTRODUCTION

FREQUENCY multipliers, and in particular frequency doublers, are important building blocks for many applications, as well as for measurement equipment. The progress of semiconductor technologies based on both specific materials and proper scaling of devices enables us to contemplate high-speed broad-band system applications up to 100 GHz. Design and measurement of such high-speed circuits present important challenges. Specific design methodology should be applied. For measurement, high-frequency sources are necessary but the usual sources such as manufacturer synthesizers are limited to 60 GHz.

Broad-band active frequency doublers have been described in Si BJT at 12 GHz [1], in SiGe heterojunction bipolar transistor (HBT) at 42 GHz with 8.6-dB gain [2], and in GaAs pseudomorphic high electron-mobility transistor (pHEMT) at 50 GHz with 5-dB loss [3]. Also, other monolithic microwave (MMIC) V -band frequency doublers have been reported (see [4, Table I]), but these circuits have a limited band of operation. Indeed, their -3 -dB output power bandwidth is, in the best case, around 30%. We can note for very high-frequency applications a MMIC doubler in InP HEMT at 164 GHz with 2-dB loss and 8.5% bandwidth [5] dedicated to narrow-band applications.

In this paper, we present the design, fabrication, and characterization of broad-band frequency doublers operating from dc

to 100 GHz. To implement these frequency doublers, we have chosen a Gilbert multiplier structure [6]. This double-balanced architecture allows us to achieve good fundamental and odd-harmonics rejection. We have designed three doubler versions. One of them is composed of a Gilbert cell with an input active splitter to achieve multiplication up to 100 GHz. To the authors' knowledge, this is the highest frequency of operation for a broad-band active frequency doubler in any technology.

The InP double heterojunction bipolar transistor (DHBT) technology, used for doubler fabrication, is presented in Section II, the doubler design in Section III, and measurement results up to 100 GHz and comparisons in Section IV.

Preliminary results of this study were presented in [7].

II. TECHNOLOGY

The InP–InGaAs DHBT technology presents several attractive aspects for the fabrication of high-speed circuits.

The very high-frequency characteristics are due to excellent electron transport properties of InP and InGaAs; the small bandgap of InGaAs base results in a low turn-on voltage, which means a potential for low power consumption; the double heterojunction gives a high breakdown voltage ($BV_{CEO} > 7$ V), necessary for large-signal applications such as optical modulator drivers; finally, the vertical technological process yields a very good built-in threshold voltage uniformity, which is very convenient for differential bipolar logics such as current-mode logic (CML) and emitter-coupled logic (ECL).

The in-house InP–InGaAs self-aligned DHBT technology was presented in [8]. F_t of 150–180 GHz and F_{max} of 210–220 GHz are currently obtained on circuit-oriented devices at a current density of about 2 mA/ μm^2 . Three Ti/Au interconnection levels, TaN resistors, MIM capacitors, and spiral inductors are also available to realize the circuit layout.

In Fig. 1, F_t and F_{max} frequencies for $2 \times 3 \mu\text{m}^2$ and $2 \times 10 \mu\text{m}^2$ emitter transistors are compared as a function of collector current. F_t above 100 GHz and F_{max} over 170 GHz are achieved for currents of 2 mA and up. This means that low-power high-frequency operation can be targeted.

III. CIRCUIT DESIGN

The frequency doubler is based on a Gilbert cell with both inputs connected together, as shown in Fig. 2. Frequency multiplication results in generating harmonics due to nonlinear characteristics of the transistors in the Gilbert cell.

Manuscript received April 23, 2004; revised July 8, 2004.

V. Puyal is with OPTO+, ALCATEL Research and Innovation, F-91461 Marcoussis, France and also with the Laboratoire de Robotique, d'Informatique et de Microélectronique de Montpellier, 34392 Montpellier, France (e-mail: vincent.puyal@alcatel.fr).

A. Konczykowska, S. Blayac, F. Jorge, M. Riet, and J. Godin are with OPTO+, ALCATEL Research and Innovation, F-91461 Marcoussis, France.

P. Nouet and S. Bernard are with the Laboratoire de Robotique, d'Informatique et de Microélectronique de Montpellier, 34392 Montpellier, France.

Digital Object Identifier 10.1109/TMTT.2005.845766




Fig. 1. F_t and F_{max} for 2×3 and $2 \times 10 \mu\text{m}^2$ emitter transistors.




Fig. 2. Gilbert cell as a frequency doubler.

A. Electrical Design

The first goal of this design was the high frequency of operation (up to 100 GHz). Three integrated doubler versions have been designed. The first version (V1) is the usual Gilbert cell. The second version (V2) adds a peaking inductor on the output in order to improve output-doubler amplitude at high frequencies [9], [10].

Usually, frequency doublers based on the Gilbert-cell structure use an external frequency splitter to provide the necessary two symmetrical inputs. This is the case for versions V1 and V2. In the last version (V3), we decided to circumvent this problem by using an internal splitter. Only one RF input signal is thus needed plus a reference dc value (REF). Still, the design and layout of version V3 offer the possibility to work in differential mode, i.e., with two symmetrical input signals.

Doubler block diagrams are presented in Fig. 3. The top diagram represents V1 and V2 versions, while the bottom graph shows the V3 version. In this version, the IN input signal is transformed by the input active splitter into two symmetrical signals (OUT1 and OUT2). These two signals enter on RF and local oscillator (LO) Gilbert cell inputs. They are converted by the cell into an IF output signal of double frequency while the fundamental frequency is suppressed.

Fig. 4 shows electrical schemes of frequency doublers.

The first version (V1), to serve as a reference, presents two stages: the emitter followers and the Gilbert cell. The circuit is composed of two pairs of emitter followers that feed the LO lower differential pair and one emitter follower pair connected to the RF upper differential pairs (Gilbert cell). These emitter follower stages realize a level shifting and impedance matching. Frequency multiplication occurs in the differential pair stage.




Fig. 3. Block diagrams of frequency doublers with (top) external splitter and (bottom) internal splitter.

Current mirrors act as stable current sources. All transistor sizes are optimized for the maximum frequency performance. Switch transistors (emitter size $2 \times 10 \mu\text{m}^2$) operating at $1.5\text{-mA}/\mu\text{m}^2$ collector current density are used. For biasing, larger transistors (emitter size $2 \times 15 \mu\text{m}^2$) are chosen. No output buffer is used: to optimize output swing at high frequencies, the doubler output is directly connected to the Gilbert cell output. In contrast to most Gilbert cells, we have chosen to use only one Gilbert cell output to minimize layout parasitics. Even if the bandwidth power is half of that of a differential output, post-layout simulation demonstrates that, for a single-ended application, the use of an asymmetrical output architecture increases the bandwidth thanks to a strong reduction of output parasitic capacitances.

The peaking inductor of the second version (V2) has been realized with a grounded coplanar waveguide (GCPW) line. The GCPW line equivalent inductance is about 200 pH.

The active splitter of the third version (V3) is composed of a differential amplifier with feedback resistors that provides broad-band amplification (Cherry–Hooper topology [11]). Emitter degeneration is used in the amplifier to linearize output splitter signals.

B. Layout Design

A microphotograph of the V3 doubler circuit is presented in Fig. 5. The chip dimensions are $1400 \times 1600 \mu\text{m}^2$.

Signal lines (two inputs) are fed via matched $50\text{-}\Omega$ GCPW lines. Similarly, the output signal is connected to output pads with $50\text{-}\Omega$ GCPW lines. The signal part of the layout is compacted to shorten high-frequency paths. The circuit core is optimized for minimum wire length and maximum symmetry. The core footprint is $250 \times 350 \mu\text{m}^2$. DC-bias connections are decoupled on-wafer with RC circuits.

As mentioned before, this circuit can be fed with two symmetrical input signals. Indeed, the GCPW line has been used on the REF pad to allow operation with both internal and external splitter modes.




Fig. 4. Electrical schemes of frequency doublers. (V1) Reference doubler. (V2) Doubler with peaking inductor. (V3) Doubler with active splitter.




Fig. 5. Microphotograph of the fabricated V3 doubler.

IV. MEASUREMENT RESULTS AND COMPARISONS

After presentation of simulation tools and measurement equipment, V1 and V2 doubler measurements are shown and compared with simulations. Next, a comparative performance graph between the three versions is given. Finally, results of the best version are detailed.

A. Simulation Tools and HBT Model

The design of integrated circuits (ICs) operating at very high frequencies needs adequate methodology at the electrical as well as at the layout level.

To evaluate correct operation, precise transient simulations have been used. These simulations should be based on correct models for active, passive, and parasitic elements.

Particular attention has been paid to transistor models. Limitations of the popular Gummel-Poon bipolar transistor model when applied to III-V compound transistors are now well identified.

In the presented design, we used the University of California at San Diego (UCSD) HBT model which allows us to implement the most important features of III-V compound transistors necessary for the correct simulation of high-speed circuits [12], [13].

B. Measurement Setup

The characterization of the frequency doubler requires adequate measurement equipment as well as special care in the measurement setup. The doubler characteristics were measured using on-wafer probing and bias lines. The measurement setup is composed as follows.




Fig. 6. Simulated V1 output amplitude and V2 output amplitude versus output frequency. Input power is -8 dBm.

A frequency synthesizer provides a signal up to 60 GHz. Output signal waveform is displayed on an oscilloscope.

The 65-GHz probes are used at the circuit output. Measurements are realized with a remote sampling head (70 GHz) and very short cables. The use of a precision timebase module allows us to characterize precisely the time jitter of the doubler.

It is clear from the equipment characteristics that, above 70 GHz. Our measurements are cumulating hard-to-estimate losses from different measurement elements (e.g., probes, cables, and sampling head). Indeed, e.g., the sampling head data sheet shows the frequency response up to 70 GHz. At 70 GHz, head losses are about 2.6 dB, but it is very difficult to extrapolate its behavior above 70 GHz. In the best case, extrapolation is linear, but, in the worse case, a bandwidth hole may appear, and, thus, losses can be very important. Measurements were realized in spite of these limitations. In consequence, experimental results above 70 GHz cannot be guaranteed, but we can estimate the actual bandwidth of the doubler as higher than the measured one.

V1, V2, and V3 doublers were characterized by applying RF signals on IN1 and IN2 pads (external splitter mode). V3 was characterized also by applying an RF signal on IN1 (IN) pad and a dc reference voltage signal on IN2 (REF) pad (internal splitter mode).

The VEE bias voltage was -4.5 V.

C. Inductive Peaking Effect

In this section, we present results from the inductor addition on the output of the Gilbert cell. Fig. 6 shows simulation of V1 and V2 output amplitudes' output frequency.

Above a 20-GHz output frequency, inductive peaking effect is important. For -8 -dBm input power, V1 amplitude is around 150 mV_{pp} whereas V2 amplitude is around 200 mV_{pp}.

V1 and V2 doublers have been measured at 40 and 80 GHz (output frequency). Comparison between simulated and measured V2 and V1 output amplitude is shown in Fig. 7. Inductive peaking effect on output amplitude in the frequency range 40–80 GHz can be summarized as multiplication by a factor of 1.3, which agrees with the simulation.




Fig. 7. V2/V1 output amplitude ratio versus frequency: inductive peaking result.




Fig. 8. Doubler performance measurement comparison. V1, V2, and V3 differential mode; V3* reference mode.

D. General Comparison

Fig. 8 summarizes the measured performance of different doubler versions. Reference output amplitude is 158 mV_{pp} and input power -8 dBm.

As pointed out before, we observe a V2 amplitude increase (1.3) due to inductive peaking.

Let us analyze the effect of the active splitter. Two measurement modes of V3 were realized: V3 (external splitter mode—differential operation) and V3* (internal splitter mode—referenced operation). We can note that the ratio between V3 and V3* changes from 40 to 80 GHz. The V3* mode of operation is more advantageous for higher frequencies. The explanation of this fact is as follows: when operating with an external splitter (V3*), we need cables and delay lines which have a limited bandwidth. These additional elements induce signal degradation at higher frequencies, making operation with an internal splitter more advantageous. However, at lower frequencies (40 GHz), differential operation results in better output signal amplitude than does the referenced one. At 80 GHz, we observe a V3* amplitude increase of factor 3 compared to the reference version V1.

We can note a large difference between measured and simulated V1 and V2 amplitudes at 80-GHz output frequency. This is




Fig. 9. Measured conversion gain versus output frequency for -8 -dBm input power ($V3^*$).




Fig. 10. Measured (top) input and (bottom) output waveforms at 100 GHz ($V3^*$).

mainly due to bench losses for frequencies greater than 70 GHz. In fact, these discrepancies demonstrate that, when an external splitter is used ($V1$, $V2$, and $V3$), a strong attenuation is measured between 40–80 GHz, while the referenced doubler ($V3^*$) is nearly constant over this band.

$V1$ and $V2$ frequency doublers consume 150 mW. The $V3$ frequency doubler consumes 730 mW shared between the active splitter (580 mW) and the multiplier (Gilbert cell) core (150 mW).

E. Measurements of a Doubler With an Active Splitter

Following the reported comparison, more in-depth measurements were carried on the active splitter doubler with internal splitter mode ($V3^*$).

In Fig. 9, the conversion gain versus output frequency is shown for -8 -dBm input power.

As already mentioned, above 70 GHz, the conversion gain is certainly underestimated because of measurement bench losses. The actual 3-dB bandwidth is then greater than the measured dc–86 GHz.

Fig. 10 shows the 50-GHz input signal and the 100-GHz output signal of the $V3^*$ frequency doubler. The rms timing




Fig. 11. Measured output power and conversion gain versus input power at 60 GHz ($V3^*$).




Fig. 12. Measured suppression of fundamental frequency versus output frequency ($V3^*$). Input power is -8 dBm.

jitter of the output signal is 390 fs, which is comparable to the 420-fs rms timing jitter of the input signal. Due to measurement bench losses, the actual output signal amplitude is greater than the measured 41 mV_{pp}.

In Fig. 11, output power and conversion gain versus input power are presented at 60 GHz. For input power values larger than -12 dBm, the doubler is in saturation mode. The maximum output power is -10 dBm. A maximum of $+1$ -dB gain is achieved at -12 -dBm input power.

In Fig. 12, we now present measurements of fundamental suppression in the whole frequency range of operation.

The fundamental and second harmonic are measured using a spectrum analyzer up to 50 GHz. Above 50 GHz, fundamental power is measured with spectrum analyzer and second-harmonic power is measured as an oscilloscope output waveform.

Up to 100 GHz, the fundamental signal is suppressed to the desired spectrum with more than 24 dB. The circuit presents an optimum rejection of fundamental signal of 32 dB at 50 GHz.

V. CONCLUSION

In this paper, we presented the design, fabrication, and characterization of broad-band frequency doublers operating at the

upper limit of the state of the art in the dc-100-GHz frequency range. A Gilbert cell with integrated active-splitter architecture allowed us to obtain such a high frequency of operation. The fundamental signal suppression in the whole frequency range is better than 24 dB. At 60 GHz, the maximum conversion gain is 1 dB. These results were obtained in spite of measurement equipment limitations. Also, combination of inductive peaking and active splitting on the same frequency doubler should further enhance the doubler performance.

ACKNOWLEDGMENT

The authors would like to thank P. Berdaguer and M. Kahn for technology, S. Vuye for measurement, S. Withitsoonthorn for useful discussions, and J. Moulu for computer-aided design (CAD) assistance, all of OPTO+, ALCATEL Research and Innovation, Marcoussis, France.

REFERENCES

- [1] P. Weger, G. Schultes, L. Treitinger, E. Bertagnolli, and K. Ehinger, "Gilbert multiplier as an active mixer with conversion gain bandwidth of up to 17 GHz," *Electron. Lett.*, vol. 27, no. 7, pp. 570-571, Mar. 1991.
- [2] S. Hackl and J. Bock, "42 GHz active frequency doubler in SiGe bipolar technology," in *Proc. 3rd Int. Microwave Millimeter-Wave Technology*, Aug. 2002, pp. 54-57.
- [3] K.-L. Deng and H. Wang, "A miniature broad-band pHEMT MMIC balanced distributed doubler," *IEEE Trans. Microw. Theory Tech.*, vol. 51, no. 4, pp. 1257-1261, Apr. 2003.
- [4] K. Nishikawa, B. Piernas, T. Nakagawa, and K. Araki, "Miniaturized and broadband V-band balanced frequency doubler for highly integrated 3-D MMIC," in *IEEE MTT-S Int. Microwave Symp. Dig.*, vol. 4, Jun. 2002, pp. 351-354.
- [5] V. Radisic, M. Micovic, M. Hu, P. Janke, C. Ngo, L. Nguyen, L. Samoska, and M. Morgan, "164-GHz MMIC HEMT doubler," *IEEE Microw. Compon. Lett.*, vol. 11, no. 6, pp. 241-243, Jun. 2001.
- [6] B. Gilbert, "A precise four-quadrant multiplier with subnanosecond response," *IEEE J. Solid-State Circuits*, vol. SSC-3, no. 4, pp. 365-373, Dec. 1968.
- [7] V. Puyal, A. Konczykowska, P. Nouet, S. Bernard, S. Blayac, F. Jorge, M. Riet, and J. Godin, "A DC-100 GHz frequency doubler in InP DHBT technology," in *IEEE MTT-S Int. Microwave Symp. Dig.*, Fort Worth, TX, Jun. 2004, pp. 167-170.
- [8] S. Blayac, M. Riet, J. L. Benchimol, F. Alexandre, P. Berdaguer, M. Kahn, A. Piquier, E. Dutisseuil, J. Moulu, A. E. Kasbari, A. Konczykowska, and J. Godin, "MSI InP/InGaAs DHBT technology: Beyond 40 Gbit/s circuits," in *Proc. 14th Indium Phosphide Related Materials Conf.*, vol. B1-4, Stockholm, Sweden, May 2002, pp. 51-54.
- [9] S. H. Park, D. Y. Jung, and C. S. Park, "Bandwidth extension in preamplifier design maintaining low power consumption," in *Proc. 3rd Int. Conf. Microwave Millimeter Wave Technology*, Aug. 2002, pp. 936-939.
- [10] B. Razavi, "Prospects of CMOS technology for high-speed optical communication circuits," *IEEE J. Solid-State Circuits*, vol. 37, no. 9, pp. 1135-1145, Sep. 2002.
- [11] E. M. Cherry and D. E. Hooper, "The design of wide-band transistor feedback amplifiers," *Proc. Inst. Elect. Eng.*, vol. 110, pp. 375-389, Feb. 1963.
- [12] A. Konczykowska, S. Blayac, F. Jorge, M. Riet, V. Puyal, and J. Godin, "Design and measurement of very high bitrate digital IC's fabricated in InP HBT technology," in *IEEE MTT-S Int. Microwave Symp. Dig.*, vol. 2, Jun. 2002, pp. 1177-1180.
- [13] L. Camnitz, S. Kofol, T. Low, and S. R. Bahl, "An accurate, large signal, high frequency model for GaAs HBTs," in *Proc. 18th GaAs Integrated Circuits Symp.*, Orlando, FL, Nov. 1996, pp. 303-306.



Vincent Puyal (S'04) received the B.S. degree in electronics engineering from Polytech Montpellier, University of Montpellier II, Montpellier, France, in 2002, and is currently working toward the Ph.D. degree in microelectronics engineering at the University of Montpellier II, Montpellier, France, in collaboration with the Laboratoire de Robotique, d'Informatique et de Microélectronique de Montpellier (LIRMM), Montpellier, and OPTO+, ALCATEL Research and Innovation, Marcoussis, France.

His current research interests include design and testing of high-speed bipolar ICs for optical communication systems.



Agnieszka Konczykowska (M'88-SM'97) received the M.S. degree in applied mathematics and Ph.D. degree in electrical engineering from the Warsaw University of Technology, Warsaw, Poland, in 1971 and 1977, respectively.

From 1971 to 1982, she was with the Warsaw University of Technology. She was with the France Telecom Research Center. Since 2001, she has been the Leader of the High Speed Circuits Group, OPTO+, ALCATEL Research and Innovation, Marcoussis, France. She has coauthored over 150 scientific publications. She has been involved with different domains of computer-aided design (CAD) and design methodologies such as methods and applications of symbolic analysis, semiconductor device modeling, and analysis and design of switched-capacitor circuits. Her current research interests are linked with circuit design of very high-speed digital circuits for optical communications in InP HBT technology. She is a member of the Editorial Board of the *International Journal of Circuit Theory and Applications*.

Dr. Konczykowska is a member of numerous technical committees of international conferences and serves as reviewer for numerous technical journals. From 1995 to 1999 she has been the president of the European Circuit Society.



Pascal Nouet (M'94) received the Maîtrise of electrical engineering, Diplôme d'Etudes Approfondies, and the Ph.D. degree in microelectronics from the University of Montpellier, Montpellier, France, in 1987, 1988, and 1991, respectively.

Since 1992, he has been a Researcher with the Laboratoire de Robotique, d'Informatique et de Microélectronique de Montpellier (LIRMM), Montpellier, France, and an Associate Professor with the University of Montpellier. His current research interests concern process characterization, analog IC design, and microsystems.



Serge Bernard (S'01-A'01-M'04) received the M.S. degree in electrical engineering from the University of Paris XI, Paris, France, in 1998, and the Ph.D. degree in electrical engineering from the University of Montpellier, Montpellier, France, in 2001.

He is currently a Researcher with the National Council of Scientific Research (CNRS), Microelectronics Department, Laboratoire de Robotique, d'Informatique et de Microélectronique de Montpellier (LIRMM), Montpellier, France. His main research interests include the design, test, and built-in self-test for mixed-signal circuits and design for reliability for medical application ICs.



Sylvain Blayac was born in Montpellier, France, in 1972. He received the M.Sc. and Diplôme d'Etudes Approfondies degrees in electronics from the University of Montpellier, Montpellier, France, in 1995 and 1996, respectively, and is currently working toward the Ph.D. degree at OPTO+, ALCATEL Research and Innovation, Marcoussis, France.

His research is focused on III-V component design and technology for high bit-rate communication circuits.



Filipe Jorge was born in Roubaix, France, in 1970. He received the Ph.D. degree in electronic engineering from the University of Lille 1, Villeneuve d'Ascq, France, in 1999.

In 2000, he joined OPTO+, ALCATEL Research and Innovation, Marcoussis, France, as a Research and Development Engineer. He is currently involved in module design and characterization of high-speed circuits for optical communication systems.



Muriel Riet was born in Choisy-le-Roi, France, in 1958. She received the Ph.D. degree in electronic engineering from the University of Paris XI, Paris, France, in 1985.

In 1985, she joined the Centre National d'Etudes des Télécommunications (CNET) (Research Center of France Telecom), where she has studied compound semiconductor HBTs. She is currently in charge of InP HBT technology for high bit-rate optical communications up to 40 Gb/s with OPTO+, ALCATEL Research and Innovation, Marcoussis, France.



Jean Godin was born in 1954. He graduated from the École Polytechnique, Paris, France, in 1975, and from the École Nationale Supérieure des Télécommunications, Paris, France, in 1978.

In 1978, he joined the Centre National d'Etudes des Télécommunications (CNET) (now France Telecom Research and Development), where he was involved in digital-signal-processing developments, based particularly on Si- and III-V charge-coupled devices (CCDs). Since 1985, he has been in charge of CAD support and developments for the laboratory, particularly for HBT very high-speed integrated circuit (VHSIC) design. Since 1995, he has led a department in charge of developments in HBT technology and circuits design. This department is now part of OPTO+, ALCATEL Research and Innovation, Marcoussis, France. His main interests are VHSIC CAD methodology and III-V circuits for very high bit-rate optical communications.